

# Addressable Android Fire Alarm Repeater Panel With Voice Alarm

Model No - AN101RP



## Overview:

This repeater panel repeats all the fault and fire messages of that of the main control panel and provide all the necessary information available at the control panel to the advantage of the end-user at a remote location. Repeater panel has a interactive display with touch screen control.Total system works on 24V DC. Panel has built in 230V to 24V power supply unit. This unit has built in battery charger and provision for SMF battery.

## Specification

### Electrical Specifications

<b>Primary Power</b>	110V/220V±10% AC, 60/50Hz
<b>Standby Power</b>	24V DC (12V, 7Ah SLA Battery,2Nos)
<b>Charging Voltage</b>	28 ± 1V
<b>Charging Current</b>	330mA (max)
<b>Operating Temperature</b>	0° C to 49° C
<b>Humidity</b>	0-95% RH (Non-condensing)

### Fuses

<b>Supply Fuse</b>	3 A Resettable fuse
<b>Battery Fuse</b>	3 A Resettable fuse

### Finish

<b>Enclosure Dimensions (HxWxD)</b>	460x390X130 mm
<b>Housing Material</b>	16 Gauge Cold Rolled sheet
<b>Back Box</b>	Black Matte
<b>Front Door</b>	Texture Red
<b>Display Resolution</b>	800X480 Pixels
<b>Display Size</b>	7"
<b>Compatibility</b>	AU101X/ AUAA2X / ALPA2XV1 / ALAW2XV1 Protocol

### Complied with:

