

# Digital Addressable Public Address System Control Panel-1 Channel

Model No - AN101PAVA



## Overview:

This Digital Addressable Public address System Control Panel is designed to operate voice system. Voice system includes public address, music, and automated voice message player. It transmits and process digital voice signal to field digital speakers and also performs two-way communications. The connected devices can be individually identified and controlled from the panel. This unit has built in battery charger and provision for SMF battery.

- Soft Addressing
- Individual / group speaker control.
- 3 way voice input
- Built-in Voice alarm with pre-recorded messages
- Corrosion protection

## Specification

### Electrical Specifications

<b>Primary Power</b>	110V/220V±10% AC, 60/50Hz
<b>Standby Power</b>	24V DC (12V, 7Ah SLA Battery, 2Nos)
<b>Charging Voltage</b>	27 ± 1V
<b>Charging Current</b>	1A (max)
<b>Operating Temperature</b>	0° C to 49° C
<b>No Of Zones</b>	32(Max)
<b>No of Channel</b>	1
<b>Addressable speaker /mic</b>	12/loop

### Fuses

<b>Supply Fuse</b>	3 A Resettable fuse
<b>Battery Fuse</b>	3 A Resettable fuse
<b>Display Resolution</b>	800X480 Pixels
<b>Display Size</b>	7"
<b>Finish</b>	
<b>Enclosure Dimensions (HxWxD)</b>	460x390X130 mm
<b>Housing Material</b>	16 Gauge Cold Rolled sheet
<b>Back Box</b>	Black Matte
<b>Front Door</b>	Texture Red
<b>Compatibility</b>	AU101X/ AUAA2X / ALPA2XV1 / ALAW2XV1 Protocol