

Digital Addressable Public Address System Control Panel-9 Channel

Model No - AN109PAVA



Overview:

This Digital Addressable Public address System Control Panel is designed to operate voice system. Voice system includes public address, music, and automated voice message player. It transmits and process digital voice signal to field digital speakers and also performs two-way communications. The connected devices can be individually identified and controlled from the panel. This unit has built in battery charger and provision for SMF battery.

- Soft Addressing
- Individual / group speaker control.
- 3 way voice input
- Built-in Voice alarm with pre-recorded messages
- Corrosion protection

Specification

Electrical Specifications

Primary Power	110V/220V±10% AC, 60/50Hz
Standby Power	24V DC (12V, 7Ah SLA Battery,2Nos)
Charging Voltage	27 ± 1V
Charging Current	1A (max)
Operating Temperature	0° C to 49° C
No Of Zones	32(Max)
No of Channel	9
Addressable speaker /mic	12/loop

Fuses

Supply Fuse	3 A Resettable fuse
Battery Fuse	3 A Resettable fuse
Display Resolution	800X480 Pixels
Display Size	7"
Finish	
Enclosure Dimensions (HxWxD)	460x390X130 mm
Housing Material	16 Gauge Cold Rolled sheet
Back Box	Black Matte
Front Door	Texture Red
Compatibility	AU101X/ AUAA2X / ALPA2XV1 / ALAW2XV1 Protocol